

1021nm PM BP Filter/Tap Hybrid

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters	Unit	Value	
Center Wavelength	nm	1021	
Min. Pass Band Width @ 0.5dB	nm	6.0	
Excess Loss	dB	≤1.6	
Stop Wavelength (ASE)	nm	1000~1015&1027~1100	
Stop Wavelength (ASE) Isolation	dB	Standard: ≥25; High Isolation ≥45	
Tap Ratio	%	1+/-0.6%, 2+/-0.8%, 5+/-1.0%, 10%, 20%, 30%, 50%	
Tap Position	F Type	-	Tap is before Bandpass Filter, Y Type (3-port), Both axis working
	S Type	-	Tap is before Bandpass Filter, Y Type (3-port), Only Slow axis working
	B Type	-	Tap is after Bandpass Filter, Y Type (3-port), Only slow axis working
	X Type	-	Tap is after Bandpass Filter, 4-port, Only Slow axis working (Blocked Wavelength Guide Out)
Optical Return Loss	dB	≥50	
Extinction Ratio	dB	≥18	
Fiber Type	Input&Output	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
	Tap Port or 4 th Port	-	Same Fiber, Corr. SM Fiber or MM Fiber
Fiber Tensile Load	N	5	
Max. Optical Power (CW)	mW	300	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package	Stainless Steel Tube (SST)	mm	∅5.5xL40 (≤5W); ∅6.0xL50 (5~10W)
Dimension	Metal Box	mm	L120x ^W 12x ^H 10 (≤10W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

Bandwidth	ASE Iso	Tap Ratio	Position	Tap Port Fiber	4th Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
60~6nm	I=High	01=1%	F=F Type	Y=Same Fiber	Y=Same Fiber	M=Metal Box	2=PM980Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	Isolation	05=5%	S=S Type	S=Corr. SM Fiber	S=Corr. SM Fiber	Blank for SST	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	Blank for	10=10%	X=X Type	S=50/125um Fiber	S=50/125um Fiber		Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	Standard	50=50%	Blank for B Type		Blank for F/S/B Type		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector