


PM DWDM Multi-Channel Mux/Demux Module for Pulse Power

FEATURES

- High Isolation
- Low Insertion Loss
- Epoxy-Free Optical Path
- High Reliability and Stability
- Low Profile Packaging

APPLICATIONS

- Broadband Systems
- Optical Add/Drop Multiplexing
- Telecommunication Networks
- Metro Networks
- DWDM Systems



SPECIFICATIONS

Parameters	Unit	Value				
		4-Ch	8-Ch	16-Ch	32-Ch	
Center Wavelength	nm	1528-1640, ITU Grid				
Channel Spacing	Hz	100G / 200G				
Channel Passband Width	nm	+/-0.11 / +/-0.25				
Insertion Loss	100G	dB	≤2.5	≤4.0	≤6.0	≤6.5
	200G	dB	≤2.2	≤3.5	≤5.5	≤6.0
Adjacent Channel Isolation	dB	≥25 for DeMux, ≥15 for Mux				
Non-adjacent Channel Isolation	dB	≥40 for Demux, ≥25 for Mux				
Pass Channel Ripple	dB	≤0.5				
Channel Uniformity	dB	≤1.0	≤1.5	≤2.0		
Optical Return Loss	dB	≥45				
Directivity	dB	≥50				
Extinction Ratio	B Type	dB	≥18		≥16	
	F Type	dB	≥20			
Working Mode	B Type	dB	Can work both in Fast Axis and Slow Axis			
	F Type	dB	Can only work in Slow Axis and Fast Axis is blocked			
Fiber Type	-	PM1550 Panda Fiber or 10/125um PMDC Fiber (O) 12/130um PMDC Fiber (T), 20/130um PMDC Fiber (Q) 25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)				
Fiber Tensile Load	N	5				
Max. Average Optical Power	W	0.3, 0.5, 1, 2, 3, 5				
Max. Peak Power for Pulse	kW	0.1, 1, 2, 3, 5, 10, 15, 20				
Operating Temperature	°C	0~50				
Storage Temperature	°C	-40~85				
Package Dimension	mm	L160x ^W 140x ^H 10		L160x ^W 160x ^H 10	L160x ^W 160x ^H 20	

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.

3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.

4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FDMP-N	C	C	C	-CNN	-H NN	P NN	-C	C	NN	-CC/CCC
Channel Spacing	Channel Number	Type	Work Mode	Starting Ch. No.	Average Power	Peak Power	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1= 100GHz	4= 4-Channel	M= Mux	B= B Type	C34= C34 Channel	03=300mW	01=100W	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
2= 200GHz	8= 8-Channel	D= DeMux	F= F Type	H40= H40 Channel	1= 1W	1= 1kW	0=10/125 PMDC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	H= 16-Channel			L00= L00 Channel	2=2W	10=10kW	T=12/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	T= 32-Channel			Q90= Q90 Channel	5=5W	20=20kW	G=25/300 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector

