

## 1537nm High Power Bandpass Filter

### FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

### APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



### SPECIFICATIONS

Parameters	Unit	Value
Center Wavelength	nm	1537
Min. Pass Band Width @ 0.5dB	nm	0.12, 0.3, 0.7, 2.0
Insertion Loss over Pass Band Wavelength	dB	≤1.2
Stop Wavelength (ASE)	0.12nm Bandwidth	1500~1536.4 & 1537.6~1600
	0.3nm Bandwidth	1500~1536 & 1538-1600
	0.7nm Bandwidth	1500~1535.5 & 1538.5-1600
	2nm Bandwidth	1500~1534 & 1540-1600
Stop Wavelength (ASE)	Standard	≥25
Isolation	High Isolation	≥45
ASE Direction	-	F: Forward, B: Backward, T: Two-way
Configuration	-	D: 2-port, Y: 3-port, X: 4-port
Optical Return Loss	dB	≥50
Polarization Dependent Loss	dB	≤0.15
Fiber Type	Input&Output	SMF-28 Fiber or 10/130um DC Fiber NA=0.08 (O) 10/130um DC Fiber NA=0.15 (O2) or 12/130um DC Fiber (T) 25/250um DC Fiber (R) or 25/300um DC Fiber (G)
	ASE Guide Out (Y/X Type)	Same Fiber or MM Fiber
Fiber Tensile Load	N	5
Max. Optical Power (CW, ASE+Signal)	W	1, 2, 3, 5, 10, 15, 20, 30, 50, 60, 80, 100
Max. ASE Optical Power (CW)	W	0.3, 0.5, 1, 2, 3, 4, 5, 10
Operating Temperature	°C	0~70
Storage Temperature	°C	-40~85
Package Dimension	Stainless Steel Tube (SST)	mm ∅5.5x <sup>L</sup> 35 (≤5W); ∅6.0x <sup>L</sup> 50 (5~10W)
	Metal Box	mm H: <sup>L</sup> 90x <sup>W</sup> 12x <sup>H</sup> 10 (>10W); M: <sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10 (≤10W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
  - To add connectors, IL is 0.3dB higher, RL is 5dB lower.
  - Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
  - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
  - Package size may be different for different optical power and configurations.

### ORDERING INFORMATION (PN)

Bandwidth	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Optical Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
012=0.12nm	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	1=1W	1=1W	M=Metal Box	O=10/130 DC Fiber	B= Bare fiber	05=0.5m	N=Without Connector
03=0.3nm	T=Two-way	Isolation	A=105/125um Fiber	A=105/125um Fiber	5=5W	5=5W	H=H Box	T=12/130 DC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
07=0.7nm	Blank for Forward	Blank for	N=None	5=50/125um Fiber	10=10W	10=10W	Blank for SST	G=25/300 DC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
20=2nm		Standard	Blank for D Type	Blank for None or D Type	20=20W	Blank for 300mW		Blank for SMF-28 Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector

