

1545nm Bandpass Filter/Isolator Hybrid for Pulse Power

FEATURES

APPLICATIONS

- Low Insertion Loss
- High Reliability and Stability
- Optical Amplifying Systems ■ Telecommunication Networks




SPECIFICATIONS

Parameters	Unit	Single Stage	Dual Stage	H Stage				
Center Wavelength		nm	1545					
Min. Pass Band Width @ 0.5dB		nm	3.0, 4.0, 10.0, 12.0					
Stop Band @25dB -	3nm Bandwidth	nm	1510~1542 & 1548~1600					
	4nm Bandwidth	nm	1510 ₁	~1600				
	10nm Bandwidth	nm	1510~1537 & 1553~1600					
	12nm Bandwidth	nm	1510~1532 & 1558~1600					
Insertion Loss@23°	C	dB	≤1.3	≤1.5	≤1.7			
Signal Isolation (23	Signal Isolation (23°C)		≥28	≥22				
	D Type	-	2-port					
Configuration	Y Type	-	3-port, (Blocked Wavelength Guide Out)					
	X Type	-	4-port, (Both Block Wavelength Guide Ou					
Fiber Type at 3 rd or	Fiber Type at 3 rd or 4 th Port (Y/X Type)			Same Fiber of other ports or 50/125um MM Fiber				
	Forward Type	-	Bandpass Filter is before isolator					
ASE Direction	Backward Type	-	Bandpass Filter is after isolator					
	Twin Type	-	Bandpass Filter is at both sides of iso					
Optical Return Loss		dB	≥45					
PDL	PDL			≤0.2				
	Fiber Type		SMF-28 Fiber or 10/130um DC Fiber (O)					
Fiber Type			12/130um DC Fiber (T) or 20/130um DC Fiber (Q)					
			25/250um DC Fiber (R) or 25/300um DC Fiber (G)					
Max. Average Option	Max. Average Optical Power			2, 3, 5, 10	15, 20			
Max. Peak Power for pulse		kW	0.1, 1, 2, 3, 5, 10, 15, 20					
Operating Temperature		°C	0~50					
Storage Temperature		°C	-40~85					
Package	Stainless Steel Tube (SST)	mm	(Ø)5.5x35 (≤5W); (я	Ø)6.0x48 (5~10W)	See Drawing			
Dimension	Metal Box	mm	(L)120x(W))12x(H)10	Jee Drawing			

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

- 2. To add connectors, IL is 0.3dB higher, RL is 5dB lower.
- 3. Suggest to use Y or X type if blocked optical power is >1W.
- 4. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
- 5. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.





ORDERING INFORMATION (PN

NN C

(C) -H NN P NN (C) Stage Bandwidth ASE Type 3rd Port Fiber 4th Port Fiber Average Power Peak Power Package Fiber Typ

10	Fiber	Sleeve	Fiber	Length	Connector	Турө
	_					

C

-CC/CCC

					•		-				
S= Single Stage	30=3nm	F= Forward	Y=Same Fiber	Y=Same Fiber	03=300mW	<mark>01</mark> =100W	M=Metal Box	0= 10/130 DC Fiber	B= Bare fiber	05= 0.5m	N=Without Connector
D= Dual Stage	40-4nm	B=Backward	5=50/125um Fiber	5= 50/125um Fiber	1- 1W	1= 1kW	<i>Blank</i> for SST	T=12/130 DC Fiber	L= Loose Tube	<mark>10=</mark> 1.0m	FC/APC=FC/APC Connector
H= H Stage	100=10nm	T=Twin	<i>Blank</i> for D Type	<i>Blank</i> for D&Y Type	5= 5W	5= 5kW	or >10W	G=25/300 DC Fiber	2= 2mm Cable	<mark>15=</mark> 1.5m	LC/PC=LC/PC Connector
	<mark>120=</mark> 12nm				10=10W	<mark>10</mark> =10kW		<i>Blank</i> for SMF-28 Fiber	3= 3mm Cable	20= 2.0m	SC/UPC=SC/UPC Connector

FHBI-1545-C



- (C)