

## 2040nm High Power Bandpass Filter/Isolator Hybrid

### FEATURES

- High Isolation
- Low Insertion Loss
- Epoxy-Free Optical Path
- High Reliability and Stability

### APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Metro Networks



### SPECIFICATIONS

Parameters	Unit	Single Stage	Dual Stage	H Stage
Center Wavelength	nm	2040		
Min. Pass Band Width @ 0.5dB	nm	10.0		
Stop Band @25dB	nm	1970-2030 & 2050-2100		
Insertion Loss@23°C	dB	≤1.6	≤1.9	≤1.9
Signal Isolation (23°C)	dB	≥16	≥30	≥25
Configuration	D Type	-	2-port	
	Y Type	-	3-port, (Blocked Wavelength Guide Out)	
	X Type	-	4-port, (Both Block Wavelength Guide Out)	
Fiber Type at 3 <sup>rd</sup> or 4 <sup>th</sup> Port (Y/X Type)	-	Same Fiber of other ports or 50/125um MM Fiber		
ASE Direction	Forward Type	-	Bandpass Filter is before isolator	
	Backward Type	-	Bandpass Filter is after isolator	
	Twin Type	-	Bandpass Filter is at both sides of isolator	
Optical Return Loss	dB	≥45		
PDL	dB	≤0.2		
Fiber Type	-	SMF-28 Fiber or SM1950 Fiber (V) 10/130um DC Fiber (O) or 25/250um DC Fiber (R)		
Max. Optical Power (CW)	W	1, 2		3, 5, 10
Operating Temperature	°C	0~50		
Storage Temperature	°C	-40~85		
Package	Stainless Steel Tube (SST)	mm	(Ø)5.5x35	
Dimension	Metal Box	mm	(L)120x(W)12x(H)10	
				See Drawing

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.3dB higher, RL is 5dB lower.
  3. Suggest to use Y or X type if blocked optical power is >1W.
  4. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  5. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

### PACKAGE DIMENSION



### ORDERING INFORMATION (PN)

FHBI-2040-**C** **NN** **C** - **(C)** **(C)** -HP **NN** -**(C)** **(C)** **C** **NN** -**CC/CCC**

Stage	Bandwidth	ASE Type	3rd Port Fiber	4th Port Fiber	Optical Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
S= Single Stage	100-10nm	F= Forward	Y=Same Fiber	Y=Same Fiber	1= 1W	M= Metal Box	V= SM1950 Fiber	B= Bare fiber	05=0.5m	N=Without Connector
D= Dual Stage		B=Backward	5=50/125um Fiber	5=50/125um Fiber	3= 3W	Blank for SST	E=10/130 DC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
H= H Stage		T=Twin	Blank for D Type	Blank for D&Y Type	5= 5W	or >2W	R=25/250 DC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
					10=10W		Blank for SMF-28 Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector