



## 1550nm PM Bandpass Filter/Isolator Hybrid ( $\leq 3\text{nm BW}$ )

### FEATURES

- Low Insertion Loss
- Various Bandwidth
- High Reliability and Stability

### APPLICATIONS

- Optical Amplifying Systems
- Telecommunication Networks
- Research Labs

### SPECIFICATIONS

Parameters	Unit	Single Stage	Dual Stage
Center Wavelength	nm	1550	
Min. Pass Band Width @ 0.5dB	nm	0.3, 0.7, 2.0, 3.0	
Stop Band @ 25dB	0.3nm Bandwidth	nm	1520~1549 & 1551~1610
	0.7nm Bandwidth		1520~1548 & 1552~1610
	2nm Bandwidth		1520~1547 & 1553~1610
	3nm Bandwidth		1520~1546 & 1554~1610
Insertion Loss@23°C	dB	$\leq 1.2$	$\leq 1.4$
Signal Isolation (23°C)	dB	$\geq 30$	$\geq 45$
Configuration	D Type	-	2-port
	Y Type	-	3-port, (Blocked Wavelength Guide Out)
	X Type	-	4-port, (Both Block Wavelength Guide Out)
Fiber Type at 3 <sup>rd</sup> or 4 <sup>th</sup> Port (Y/X Type)	-	Same Fiber, Corr. SM Fiber or 50/125um MM Fiber	
ASE Direction	Forward Type	-	Bandpass Filter is before isolator
	Backward Type	-	Bandpass Filter is after isolator
	Twin Type	-	Bandpass Filter is at both sides of isolator
Optical Return Loss	dB	$\geq 45$	
Extinction Ratio	dB	$\geq 20$	
Work Mode	S Type	-	Can only work in slow axis
	F Type	-	Can work both in slow axis and fast axis
Fiber Type	-	PM1550 Panda Fiber or 10/125um PMDC Fiber (O) 12/130um PMDC Fiber (T), 20/130um PMDC Fiber (Q) 25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)	
Max. Optical Power (CW)	mW	300	
Operating Temperature	°C	0~70	
Storage Temperature	°C	-40~85	
Package	Stainless Steel Tube (SST)	mm	( $\varnothing$ )5.5x35
Dimension	Metal Box	mm	(L)120x(W)12x(H)10

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. Suggest to use Y or X type if blocked optical power is  $> 1\text{W}$ .
  4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

### ORDERING INFORMATION (PN)

Stage	Bandwidth	ASE Type	Work Mode	3rd Port Fiber	4th Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
S= Single Stage	03=0.3nm	F= Forward	S= S Type	Y=Same Fiber	Y=Same Fiber	M=Metal Box	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
D= Dual Stage	07=0.7nm	B=Backward	F= F Type	S=Corr. SM Fiber	S=Corr. SM Fiber	Blank for SST	0=10/125 PMDC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	20=2nm	T=Twin		5=50/125um Fiber	5=50/125um Fiber		T=12/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	30=3nm			Blank for D Type	Blank for D&Y Type		G=25/300 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector

