

1560nm PM Bandpass Filter/Isolator Hybrid ($\geq 10\text{nm BW}$)

FEATURES

- High Isolation
- Low Insertion Loss
- Various Bandwidth
- High Reliability and Stability

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Research Labs



SPECIFICATIONS

Parameters	Unit	Single Stage	Dual Stage
Center Wavelength	nm	1560	
Min. Pass Band Width @ 0.5dB	nm	10.0, 15.0, 20.0	
Stop Band @ 25dB	10nm Bandwidth	nm	1520~1550 & 1570~1610
	15nm Bandwidth		1520~1547 & 1573~1610
	20nm Bandwidth		1520~1545 & 1575~1610
Insertion Loss@23°C	dB	≤ 1.3	≤ 1.5
Signal Isolation (23°C)	dB	≥ 25	≥ 40
Configuration	D Type	-	2-port
	Y Type	-	3-port, (Blocked Wavelength Guide Out)
	X Type	-	4-port, (Both Block Wavelength Guide Out)
Fiber Type at 3 rd or 4 th Port (Y/X Type)	-	Same Fiber, Corr. SM Fiber or 50/125um MM Fiber	
ASE Direction	Forward Type	-	Bandpass Filter is before isolator
	Backward Type	-	Bandpass Filter is after isolator
	Twin Type	-	Bandpass Filter is at both sides of isolator
Optical Return Loss	dB	≥ 45	
Extinction Ratio	dB	≥ 20	
Work Mode	S Type	-	Can only work in slow axis
	F Type	-	Can work both in slow axis and fast axis
Fiber Type	-	PM1550 Panda Fiber or 10/125um PMDC Fiber (O) 12/130um PMDC Fiber (T), 20/130um PMDC Fiber (Q) 25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)	
Max. Optical Power (CW)	mW	300	
Operating Temperature	°C	0~70	
Storage Temperature	°C	-40~85	
Package	Stainless Steel Tube (SST)	mm	(\varnothing)5.5x35
Dimension	Metal Box	mm	(L)120x(W)12x(H)10

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - Suggest to use Y or X type if blocked optical power is $> 1\text{W}$.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

FHBP-1560-C NNN C C - (C) (C) - (C) C C NN - CC/CCC										
<i>Stage</i>	<i>Bandwidth</i>	<i>ASE Type</i>	<i>Work Mode</i>	<i>3rd Port Fiber</i>	<i>4th Port Fiber</i>	<i>Package</i>	<i>Fiber Type</i>	<i>Fiber Sleeve</i>	<i>Fiber Length</i>	<i>Connector Type</i>
S= Single Stage	100=10nm	F= Forward	S= S Type	Y=Same Fiber	Y=Same Fiber	M= Metal Box	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
D= Dual Stage	150=15nm	B=Backward	F= F Type	S=Corr. SM Fiber	S=Corr. SM Fiber	Blank for SST	0=10/125 PMDC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	200=20nm	T=Twin		5=50/125um Fiber	5=50/125um Fiber		T=12/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
				Blank for D Type	Blank for D&Y Type		G=25/300 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector