

920nm High Power BP Filter/Tap Hybrid

FEATURES

- ☑ High Isolation
- ☑ Low Insertion Loss
- ☑ High Reliability and Stability
- ☑ Various Bandwidth
- ☑ High Optical Power

APPLICATIONS

- ☑ Broadband Systems
- ☑ Optical Amplifying Systems
- ☑ Telecommunication Networks
- ☑ Laser Systems
- ☑ Research Labs



SPECIFICATIONS

Parameters	Unit	Value	
Center Wavelength	nm	920	
Min. Pass Band Width @ 0.5dB	nm	2.0	
Excess Loss	dB	≤1.6	
Stop Wavelength (ASE)	nm	850~917&923~1000	
Stop Wavelength (ASE) Isolation	dB	Standard: ≥25; High Isolation ≥45	
Tap Ratio	%	1+/-0.6%, 2+/-0.8%, 5+/-1.0%, 10%, 20%, 30%, 50%	
Tap Position	F Type (Forward)	- Tap is before Bandpass Filter, Y Type (3-port)	
Optical Return Loss	dB	≥50	
PDL	dB	≤0.15	
Fiber Type	Input&Output	HI780 Fiber, 780-HP Fiber(7), HI1060 Fiber or 10/125um SC Fiber 10/125um DC Fiber (O), 15/130um DC Fiber (W) 20/130um DC Fiber (Q) or 25/250um DC Fiber (R)	
	Tap Port	Same Fiber, HI780 Fiber or MM Fiber	
Fiber Tensile Load	N	5	
Max. Optical Power (CW)	W	1, 2, 3, 5, 10, 15, 20, 30, 40, 50, 60	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x ^L 40 (≤5W); ∅6.0x ^L 50 (5~10W)
	Metal Box	mm	^L 120x ^W 12x ^H 10 (≤10W)

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
 2. To add connectors, IL is 0.7dB higher, RL is 5dB lower.
 3. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 5. Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

FHBT-920 -NN (C) NN C - HP NN - (C) (C) C NN - CC/CCC									
Bandwidth	ASE Iso	Tap Ratio	Tap Port Fiber	Optical Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
20-2nm	I-High	01-1%	Y-Same Fiber	1-1W	M-Metal Box	H-HI1060 Fiber	B- Bare fiber	05-0.5m	N-Without Connector
	Isolation	05-5%	H-HI780 Fiber	5-5W	Blank for SST	E-10/125um SC Fiber	L- Loose Tube	10-1.0m	FC/APC=FC/APC Connector
	Blank for	10-10%	5-50/125um Fiber	10-10W	or >10W	R-25/250um DC Fiber	2- 2mm Cable	15-1.5m	LC/PC=LC/PC Connector
	Standard	50-50%		20-20W		Blank for HI780 Fiber	3- 3mm Cable	20-2.0m	SC/UPC=SC/UPC Connector