980/1030nm WDM/Isolator/Tap Hybrid

FEATURES

APPLICATIONS

- Low Insertion Loss
- **Epoxy-Free Optical Path**
- High Reliability and Stability
- Broadband Systems
- **Optical Amplifying Systems**
- Telecommunication Networks

SPECIFICATIONS

| Parameters | | Unit | Single Stage | Dual Stage | | |
|-------------------------------------|----------------------------|------|--|------------|--|--|
| Signal Wavelength Range λ1 | | nm | 1030+/-10 | | | |
| Pump Wavelength Range λ2 | | nm | 980+/-10 | | | |
| Excess Loss@23°C Signal Channel@λ1 | | dB | ≤4.6 ≤8.3 | | | |
| Insertion Loss@23°C Pump Channel@λ2 | | dB | ≤0.8 | | | |
| Signal Tap Ratio | | % | 1+/-0.5%, 2+/-0.7%, 5+/-1.0%, 10%, 20%, 30%, 50% | | | |
| Signal Isolation (23°C, All SOP) | | dB | ≥20 | ≥40 | | |
| Wayalangth Isolation | Signal Channel@λ2 | dB | ≥25 | | | |
| Wavelength Isolation | Pump Channel@λ1 | dB | ≥12 | | | |
| Optical Return Loss | | dB | ≥45 | | | |
| PDL | | dB | ≤0.3 | | | |
| Pump Direction | | ı | Forward Pump | | | |
| Fiber Type | | - | HI1060 Fiber or 10/125um SC Fiber (E) | | | |
| | | | 10/125um DC Fiber (O), 15/130um DC Fiber (W) | | | |
| | | | 20/130um DC Fiber (Q) or 25/250um DC Fiber (R) | | | |
| Fiber Tensile Load | | N | 5 | | | |
| Max. Signal Optical Power (CW) | | mW | 50 | | | |
| Max. Pump Optical Power (CW) | | mW | 0.3, 0.5, 1, 2, 3, 5, 10 | | | |
| Operating Temperature | | °C | 0~50 | | | |
| Storage Temperature | | °C | -40~85 | | | |
| Package Dimension | Stainless Steel Tube (SST) | mm | (Ø)5.5x40 | | | |
| | Metal Box | mm | (L)120x(W)12x(H)10 | | | |

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

- 2. To add connectors, IL is 0.5dB higher, RL is 5dB lower.
- 3. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

ORDERING INFORMATION (PN)

| FHWT-9803-C | NN | - (NN) | - (C) | (C) | C | NN | -CC/CCC |
|-------------|--------------------|------------------------|----------------------|-------------------------------|---------------|-----------------|-------------------------|
| Stage | Tap Ratio | Pump Power | Package | Fiber Type | Fiber Sleeve | Fiber Length | Connector Type |
| S= Single | 01= 1% | 05=500mW | M=Metal Box | E= 10/125 SC Fiber | B= Bare fiber | 05=0.5m | N=Without Connector |
| D=Dual | 05= 5% | 1-W | <i>Blank</i> for SST | Q= 20/130 DC Fiber | L= Loose Tube | 10=1.0m | FC/APC=FC/APC Connector |
| | 10=10% | 10-W | | R=25/250 DC Fiber | 2= 2mm Cable | 15=1.5m | LC/PC=LC/PC Connector |
| | 50= 50% | <i>Blank</i> for 300mW | | <i>Blank</i> for HI1060 Fiber | 3= 3mm Cable | 20 =2.0m | SC/UPC=SC/UPC Connector |





