

## 1036nm High Power PM Bandpass Filter

### FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

### APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



### SPECIFICATIONS

Parameters	Unit	Standard	High ER Type
Center Wavelength	nm	1036	
Min. Pass Band Width @ 0.5dB	nm	2.0, 12	
Insertion Loss over Pass Band Wavelength	dB	≤1.2	≤1.4
Stop Wavelength (ASE)	2nm Bandwidth	960~1031&1039~1120	
	12nm Bandwidth	960~1021&1051~1120	
Stop Wavelength (ASE)	Standard	≥25	
Isolation	High Isolation	≥45	
ASE Direction	-	F: Forward, B: Backward, T: Two-way	
Configuration	-	D: 2-port, Y: 3-port, X: 4-port	
Optical Return Loss	dB	≥50	
Extinction Ratio	dB	≥18	≥20
Fiber Type	Input&Output	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
	ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber
Fiber Tensile Load	N	5	
Max. Optical Power (CW, ASE+Signal)	W	1, 2, 3, 5, 10, 15, 20, 30, 40, 50, 60, 80, 100	
Max. ASE Optical Power (CW)	W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x <sup>L</sup> 35 (≤5W); ∅6.0x <sup>L</sup> 50 (5~10W)
	Metal Box	mm	H: <sup>L</sup> 90x <sup>W</sup> 12x <sup>H</sup> 10 (>10W); M: <sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10 (≤10W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
  - To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  - High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
  - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
  - Package size may be different for different optical power and configurations.

### ORDERING INFORMATION (PN)

FPBP-1036-NNN (C)(C) (C) (C) (C) - HP NN -(NN) - (C) C C NN -CC/CCC												
Bandwidth	Type	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Optical Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
20=2nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	1= 1W	1= 1W	M=Metal Box	2=PM980Fiber	B= Bare fiber	05=0.5m	N=Without Connector
120=12nm	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	5= 5W	5= 5W	H=H Box	E=PM1060L Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	10=10W	10=10W	Blank for SST	Q=20/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
		Standard	Blank for D Type	Blank for D Type	Blank for None or D Type	20=20W	Blank for 300mW		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector