

## 1304nm High Power PM Bandpass Filter

### FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

### APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



### SPECIFICATIONS

Parameters		Unit	Standard	High ER Type
Center Wavelength		nm	1304	
Min. Pass Band Width @ 0.5dB		nm	15.0	
Insertion Loss over Pass Band Wavelength		dB	≤1.0	≤1.2
Stop Wavelength (ASE)		nm	1250~1292 & 1316-1410	
Stop Wavelength (ASE)	Standard	dB	≥25	
Isolation	High Isolation	dB	≥45	
ASE Direction		-	F: Forward, B: Backward, T: Two-way	
Configuration		-	D: 2-port, Y: 3-port, X: 4-port	
Optical Return Loss		dB	≥50	
Extinction Ratio		dB	≥18	≥20
Fiber Type	Input&Output	-	PM1310 Panda Fiber or 10/125um PMDC Fiber NA=0.08 (O) 10/130um PMDC Fiber NA=0.15 (O2) or 12/130um PMDC Fiber (T) 25/250um PMDC Fiber (R) or 25/300um PMDC Fiber (G)	
	ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber	
Fiber Tensile Load		N	5	
Max. Optical Power (CW, ASE+Signal)		W	1, 2, 3, 5, 10, 15, 20, 30, 40, 50, 60, 80, 100	
Max. ASE Optical Power (CW)		W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature		°C	0~70	
Storage Temperature		°C	-40~85	
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x <sup>L</sup> 35 (≤5W); ∅6.0x <sup>L</sup> 50 (5~10W)	
	Metal Box	mm	H: <sup>L</sup> 90x <sup>W</sup> 12x <sup>H</sup> 10 (>10W); M: <sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10 (≤10W)	

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
  - To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  - High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
  - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
  - Package size may be different for different optical power and configurations.

### ORDERING INFORMATION (PN)

FPBP-1304- <b>NN(C)(C)(C)</b> - <b>(C)</b> <b>(C)</b> - <b>HPNN</b> - <b>(NN)</b> - <b>(C)</b> <b>C</b> <b>C</b> <b>NN</b> - <b>CC/CCC</b>												
<i>Bandwidth</i>	<i>Type</i>	<i>ASE Type</i>	<i>ASE Iso</i>	<i>Fwd ASE Fiber</i>	<i>Dwd ASE Fiber</i>	<i>Optical Power</i>	<i>ASE Power</i>	<i>Package</i>	<i>Fiber Type</i>	<i>Fiber Sleeve</i>	<i>Fiber Length</i>	<i>Connector Type</i>
150~15nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	1- 1W	1- 1W	M=Metal Box	2=PM1310Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	5- 5W	5- 5W	H=H Box	0=10/125 PMDC Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	10=10W	10=10W	Blank for SST	T=12/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
			Standard	Blank for D Type	Blank for None or D Type	20=20W	Blank for 300mW		G=25/300 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector