

## 920nm High Power PM Bandpass Filter

### FEATURES

- ▣ High Isolation
- ▣ Low Insertion Loss
- ▣ High Reliability and Stability
- ▣ Various Bandwidth
- ▣ High Optical Power

### APPLICATIONS

- ▣ Broadband Systems
- ▣ Optical Amplifying Systems
- ▣ Telecommunication Networks
- ▣ Laser Systems
- ▣ Research Labs



### SPECIFICATIONS

Parameters	Unit	Standard	High ER Type	
Center Wavelength	nm	920		
Min. Pass Band Width @ 0.5dB	nm	2.0		
Insertion Loss over Pass Band Wavelength	dB	≤1.2	≤1.4	
Stop Wavelength (ASE)	nm	850~917&923~1000		
Stop Wavelength (ASE)      Standard	dB	≥25		
Isolation      High Isolation	dB	≥45		
ASE Direction	-	F: Forward, B: Backward, T: Two-way		
Configuration	-	D: 2-port, Y: 3-port, X: 4-port		
Optical Return Loss	dB	≥50		
Extinction Ratio	dB	≥18	≥20	
Fiber Type      Input&Output	-	PM780-HP Fiber(7), PM850 Fiber, PM980 Fiber(H) or PM1060L Fiber (E)		
	-	10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W)		
ASE Guide Out (Y/X Type)	-	20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)		
ASE Guide Out (Y/X Type)	-	Same Fiber, Corr. SM Fiber or MM Fiber		
Fiber Tensile Load	N	5		
Max. Optical Power (CW, ASE+Signal)	W	1, 2, 3, 5, 10, 15, 20		
Max. ASE Optical Power (CW)	W	0.3, 0.5, 1, 2, 3, 4, 5, 10		
Operating Temperature	°C	0~50		
Storage Temperature	°C	-40~85		
Package Dimension	Stainless Steel Tube (SST)	mm	∅5.5x <sup>L</sup> 35 (≤5W); ∅6.0x <sup>L</sup> 50 (5~10W)	
	Metal Box	mm	<sup>L</sup> 90x <sup>W</sup> 12x <sup>H</sup> 10 (>10W); <sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10 (≤10W)	

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.7dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. High ER type can only work in slow axis; Suggest to use Y/X type or H Box if blocked optical power is ≥1W.
  4. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
  5. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
  6. Package size may be different for different optical power and configurations.

### ORDERING INFORMATION (PN)

FPBP-920-NN(C)(C) (C) (C) (C) - HPNN -(NN) -(C) C C NN -CC/CCC												
Bandwidth	Type	ASE Type	ASE Iso	Fwd ASE Fiber	Bwd ASE Fiber	Optical Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
20=2nm	R=High ER	B=Backward	I=High	Y=Same Fiber	Y=Same Fiber	1= 1W	1= 1W	M=Metal Box	2=PM850Fiber	B= Bare fiber	05=0.5m	N=Without Connector
	Blank for	T=Two-way	Isolation	S=Corr. SM Fiber	S=Corr. SM Fiber	5= 5W	5= 5W	H=H Box	H=PM980 Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	Standard	Blank for Forward	Blank for	N=None	A=105/125um Fiber	10=10W	10=10W	Blank for SST	E=PM1060L Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
			Standard	Blank for D Type	Blank for None or D Type	20=20W	Blank for 300mW		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector