

## 2000nm PM Filter Coupler

### FEATURES

- ▣ Low Excess Loss
- ▣ Various Splitting Ratio
- ▣ Wide Passband
- ▣ High Stability and Reliability
- ▣ Epoxy Free Optical Path

### APPLICATIONS

- ▣ Optical Amplifier
- ▣ Optical Networks
- ▣ Power Monitoring
- ▣ Fiber Sensor
- ▣ Lab



### SPECIFICATIONS

Parameter	Unit	Value						
Center Wavelength	nm	1900, 1950, 2000, 2050						
Bandwidth	nm	+/-20						
Split Ratio	-	0.1:99.9	1:99	2:98	5:95	10:90	40:60	50:50
Tap Ratio	-	0.1%	1±0.5%	2±0.6%	5±1.2%	10%	40%	50%
Excess Loss	1x2	dB	≤1.2					
	2x2	dB	≤1.4					
Uniformity	Max.	dB	1.0					
Extinction Ratio		dB	≥20					
Optical Return Loss		dB	≥50					
Fiber Type	Tap Port	-	Same Fiber, Corresponding SM Fiber or 50/125um Fiber					
	Thru Port	-	PM1550 Panda Fiber or PM1950 Fiber (V) 10/130um PMDC Fiber (O) or 25/250um PMDC Fiber (R)					
Work Mode	Standard	-	Can only work in Slow Axis					
	B Type	-	Can work both in Slow Axis and Fast Axis					
Fiber Tensile Load	N	5						
Max. Optical Power (CW)	mW	300						
Operating Temperature	°C	0~50						
Storage Temperature	°C	-40~85						
Package	Stainless Steel Tube (SST)	mm	∅5.5x <sup>L</sup> 35					
Dimension	Metal Box	mm	<sup>L</sup> 120x <sup>W</sup> 12x <sup>H</sup> 10					

**Note:** 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.

3. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

### ORDERING INFORMATION (PN)

FPFC-NNNN - NN	C	N	(C)	-(C)	C	C	NN	-CC/CCC	
Wavelength	Split Ratio	Tap Port Fiber	Type	Work Mode	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1900-1900nm	01-1/99	P= Same Fiber	1-1x2	B=B Type	M=Metal Box	2= PM1550 Fiber	B= Bare fiber	05-0.5m	N=Without Connector
1950-1950nm	05-5/95	S= Corr. SM Fiber	2-2x2	Blank for Standard	Blank for SST	V= PM1950 Fiber	L= Loose Tube	10-1.0m	FC/APC=FC/APC Connector
2000-2000nm	10-10/90	5-50/125um Fiber				O=10/130 PMDC Fiber	2= 2mm Cable	15-1.5m	LC/PC=LC/PC Connector
2050-2050nm	50-50/50					R=25/250 PMDC Fiber	3= 3mm Cable	20-2.0m	SC/UPC=SC/UPC Connector