

## 2000nm 1x5 PM Filter Splitter Module

### FEATURES

- Low Excess Loss
- Various Splitting Ratio
- Wide Passband
- High Stability and Reliability
- Epoxy Free Optical Path

### APPLICATIONS

- Optical Amplifier
- Optical Networks
- Power Monitoring
- Fiber Sensor
- Lab



### SPECIFICATIONS

Parameter	Unit	Value
Center Wavelength	nm	1900, 1950, 2000, 2050
Bandwidth	nm	+/-20nm or customer specify
Configuration	-	1x5
Split Ratio	%	Even Split
Insertion Loss	dB	≤9.4
Uniformity	dB	≤1.5
Extinction Ratio	dB	≥20
Optical Return Loss	dB	≥50
Working Mode	-	Can only work in Slow Axis
Fiber Type	-	PM1550 Panda Fiber or PM1950 Fiber (V) 10/130um PMDC Fiber (O) or 25/250um PMDC Fiber (R)
Alignment	-	Slow Axis
Fiber Tensile Load	N	5
Maximum Optical Power (CW)	mW	300
Operating Temperature	°C	0~50
Storage Temperature	°C	-40~85
Package Dimension	mm	L160x <sup>W</sup> 140x <sup>H</sup> 10

- Note:**
1. Specifications are for device without connectors; Specifications may change without notice.
  2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
  3. The devices can only work in slow axis and fast axis is blocked.
  4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

### ORDERING INFORMATION (PN)

<b>FPFM-</b>	<b>NNNN</b>	<b>- 1X5</b>	<b>- C</b>	<b>C</b>	<b>NN</b>	<b>- CC/CCC</b>
	<i>Wavelength</i>		<i>Fiber Type</i>	<i>Fiber Sleeve</i>	<i>Fiber Length</i>	<i>Connector Type</i>
	1900=1900nm		2= PM1550 Fiber	B= Bare Fiber	05=0.5m	N=Without Connector
	1950= 1950nm		V= PM1950 Fiber	L= Loose Tube	10=1.0m	FC/APC=FC/APC Connector
	2000= 2000nm		O=10/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
	2050= 2050nm		R=25/250 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector