

1013nm High Power PM BP/Partial Mirror Hybrid

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters	Unit	Standard	High ER Type
Center Wavelength	nm	1013	
Min. Bandwidth@0.5dB	nm	2.0	
Excess Loss	dB	≤1.3	≤1.5
Stop Wavelength (ASE)	nm	960~1010&1016~1100	
Stop Wavelength (ASE) Isolation	dB	Standard	≥25
	dB	High Isolation	≥45
Reflective Ratio	%	1±0.6, 2±0.8, 5±1, 10, 20, 30, 40, 50, 80, 90	
BP Position	-	Forward	Bandpass is before the Mirror
	-	Backward	Bandpass is after the Mirror
Configuration	-	D: 2-port, Y: 3-port, (Forward/Backward ASE Guide Out)	
Optical Return Loss	dB	≥45	
Extinction Ratio	dB	≥18	≥20
Fiber Type	-	Input&Output	
	-	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L)	
	-	10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W)	
	-	20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)	
	-	ASE Guide Out (Y/X Type)	
	-	Same Fiber, Corr. SM Fiber or MM Fiber	
Fiber Tensile Load	N	5	
Max. Optical Power (CW)	W	1, 2, 3, 5, 10, 15, 20, 30, 40, 50, 60, 80, 100	
Max. ASE Optical Power (CW)	W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package Dimension	mm	Stainless Steel Tube (SST)	
	mm	∅5.5x ^L 35 (≤5W); ∅6.0x ^L 50 (5~10W)	
	mm	Metal Box	
	mm	H: ^L 90x ^W 12x ^H 10 (>10W); M: ^L 120x ^W 12x ^H 10 (≤10W)	

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

2. To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.

3. High ER type can only work in slow axis at pass port; Suggest to use Y type if blocked optical power is >1W.

4. Only guarantee 1W continuous wave (CW) power thru testing for connectors added.

5. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

6. Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

Center Wavelength	Bandwidth	ASE Iso	Ref. Ratio	BP Position	Type	3rd Port Fiber	Optical Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1013-1013nm	20-2nm	I=High	01-1%	B=Backward	R=High ER	Y=Same Fiber	1-1W	1-1W	M=Metal Box	2=PM980Fiber	B=Bare fiber	05-0.5m	N=Without Connector
		Isolation	05-5%	Blank for	Blank for	S=Corr. SM Fiber	5-5W	5-5W	H=H Box	E=PM1060L Fiber	L=Loose Tube	10-1.0m	FC/APC=FC/APC Connector
		Blank for	50-50%	Forward	Standard	5=50/125um Fiber	10-10W	10-10W	Blank for SST	Q=20/130 PMDC Fiber	2=2mm Cable	15-1.5m	LC/PC=LC/PC Connector
		Standard	90-90%			Blank for D Type	20-20W	Blank for 300mW		R=25/250 PMDC Fiber	3=3mm Cable	20-2.0m	SC/UPC=SC/UPC Connector

