

1120nm PM BP/Partial Mirror Hybrid for Pulse Power

FEATURES

- High Isolation
- Low Insertion Loss
- High Reliability and Stability
- Various Bandwidth
- High Optical Power

APPLICATIONS

- Broadband Systems
- Optical Amplifying Systems
- Telecommunication Networks
- Laser Systems
- Research Labs



SPECIFICATIONS

Parameters	Unit	Standard	High ER Type
Center Wavelength	nm	1120	
Min. Bandwidth@0.5dB	nm	10.0	
Excess Loss	dB	≤1.3	≤1.5
Stop Wavelength (ASE)	nm	1030~1110&1130~1200	
Stop Wavelength (ASE) Isolation	dB	Standard	≥25
	dB	High Isolation	≥45
Reflective Ratio	%	1±0.6, 2±0.8, 5±1, 10, 20, 30, 40, 50, 80, 90	
BP Position	-	Forward	Bandpass is before the Mirror
	-	Backward	Bandpass is after the Mirror
Configuration	-	D: 2-port, Y: 3-port, (Forward/Backward ASE Guide Out)	
Optical Return Loss	dB	≥45	
Extinction Ratio	dB	≥18	≥20
Fiber Type	-	Input&Output	PM980 Fiber, PM1060L Fiber (E) or PM1060L-FA Fiber (L) 10/125um PMDC Fiber (O), 15/130um PMDC Fiber (W) 20/130um PMDC Fiber (Q) or 25/250um PMDC Fiber (R)
	-	ASE Guide Out (Y/X Type)	Same Fiber, Corr. SM Fiber or MM Fiber
Fiber Tensile Load	N	5	
Max. Average Optical Power	W	0.3, 0.5, 1, 2, 3, 5, 10, 15, 20, 30, 50, 60, 80, 100	
Max. Peak Power for pulse	kW	0.1, 1, 2, 3, 5, 10, 15, 20	
Max. ASE Average Power	W	0.3, 0.5, 1, 2, 3, 4, 5, 10	
Operating Temperature	°C	0~50	
Storage Temperature	°C	-40~85	
Package Dimension	mm	Stainless Steel Tube (SST)	∅5.5xL35 (≤5W); ∅6.0xL50 (5~10W)
	mm	Metal Box	H: L90x ^W 12x ^H 10 (>10W); M: L120x ^W 12x ^H 10 (≤10W)

- Note:**
- Specifications are for device without connectors; Specifications may change without notice.
 - To add connectors, IL is 0.5dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
 - High ER type can only work in slow axis at pass port; Suggest to use Y type if blocked optical power is >1W.
 - Only guarantee 1W continuous wave (CW) power thru testing for connectors added.
 - Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.
 - Package size may be different for different optical power and configurations.

ORDERING INFORMATION (PN)

Center Wavelength	Bandwidth	ASE Iso	Ref. Ratio	Type	BP Position	3rd Port Fiber	Average Power	Peak Power	ASE Power	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
1120-1120nm	100-10nm	I=High	O1=1%	R=High ER	B=Backward	Y=Same Fiber	O3=300mW	O1=100W	I=1W	M=Metal Box	2=PM980Fiber	B= Bare fiber	O5=0.5m	N=Without Connector
		Isolation	O5=5%	Blank for	Blank for	S=Corr. SM Fiber	I=1W	I=1kW	S=5W	H=H Box	E=PM1060L Fiber	L= Loose Tube	I=1.0m	FC/APC=FC/APC Connector
		Blank for	S=50%	Standard	Forward	S=50/125um Fiber	S=5W	S=5kW	I=10W	Blank for SST	Q=20/130 PMDC Fiber	2= 2mm Cable	I=1.5m	LC/PC=LC/PC Connector
		Standard	R=90%			Blank for D Type	I=10W	I=10kW	Blank for 300mW		R=25/250 PMDC Fiber	3= 3mm Cable	I=2.0m	SC/APC=SC/APC Connector

