

# 2000nm PM BP/Partial Mirror Hybrid

## **FEATURES**

- High Isolation
- Low Insertion Loss
- Epoxy-Free Optical Path
- High Reliability and Stability
- Low Profile Packaging

#### **APPLICATIONS**

- **Broadband Systems**
- Optical Amplifying Systems
- Telecommunication Networks
- Metro Networks
- **CATV Networks**



### **SPECIFICATIONS**

Parameters		Unit	Standard	High ER Type		
Center Wavelength		nm	2000			
Min. Bandwidth@0.5d	IB	nm	6.0			
Excess Loss		dB	≤1.5	≤1.8		
Stop Band @25dB		nm	1900-1990 & 2010-2050			
Reflective Ratio		%	1±0.6, 2±0.8, 5±1, 10, 20, 30, 40, 50, 80, 90			
Carefinance tions	D Type	-	2-port			
Configuration	Y Type	-	3-port, (Blocked Wavelength Guide Out)			
Fiber Type at 3 <sup>rd</sup> Port	(Only for Y Type)	-	Same Fiber, Corr. SM Fiber or 50/125um MM Fiber			
Optical Return Loss		dB	≥45			
Extinction Ratio		dB	≥18	≥20		
Fiber Type		-	PM1550 Panda Fiber or PM1950 Fiber (V)			
			10/130um PMDC Fiber (O) or 25/250um PMDC Fiber (R)			
Fiber Tensile Load		N	5			
Max. Optical Power (C	CW)	mW	300			
Operating Temperatu	re	°C	0~50			
Storage Temperature		°C	-40~85			
Da alvana Dimamaian	Stainless Steel Tube (SST)	mm	(Ø)5.5x35			
Package Dimension	Metal Box	mm	(L)120x(W)12x(H)10			

Note: 1. Specifications are for device without connectors; Specifications may change without notice.

- 2. To add connectors, IL is 0.3dB higher, RL is 5dB lower, ER is 2dB Lower, Connector key is aligned to slow axis.
- 3. High ER type can only work in slow axis at pass port; Suggest to use Y type if blocked optical power is >1W.
- 4. Devices for higher optical power or with other type fiber or consigned fiber are also available; Devices can only work in the core of Double Cladding (DC) Fiber, Cladding Power must be stripped before connecting the device.

## **ORDERING INFORMATION (PN)**

FPHR-NNNN	- NN	NN	- (C)	( <b>C</b> )	- ( <mark>C</mark> )	С	С	NN	-CC/CCC
Center Wavelength	Bandwidth	Ref. Ratio	Туре	3rd Port Fiber	Package	Fiber Type	Fiber Sleeve	Fiber Length	Connector Type
2000 = 2000nm	60=6nm	01-1%	R=High ER	Y=Same Fiber	M=Metal Box	2=PM1550Fiber	B= Bare fiber	05=0.5m	N=Without Connector
		05=5%	<i>Blank</i> for	S=Corr. SM Fiber	<i>Blank</i> for SST	V=PM1950 Fiber	L= Loose Tube	10-1.0m	FC/APC=FC/APC Connector
		<del>50=</del> 50%	Standard	5=50/125um Fiber		<b>0=</b> 10/130 PMDC Fiber	2= 2mm Cable	15=1.5m	LC/PC=LC/PC Connector
		90=90%		<i>Rlank</i> for D Tyne		G=25/300 PMDC Fiber	3= 3mm Cable	20=2.0m	SC/UPC=SC/UPC Connector





